AMENDMENTS TO THE CLAIMS

1. (Currently Amended) A driving ~~method for a passive liquid crystal display~~scheme for operation of a liquid crystal display comprising:

(i) a plurality of orthogonal addressing functions; ~~wherein~~

~~(ii) said plurality of orthogonal addressing functions is applied simultaneously to a plurality of rows of the said display matrix;~~

(ii~~i~~) said plurality of orthogonal addressing functions comprising a row (common) driving matrix ~~and wherein~~;

(iii) wherein said plurality of addressing functions are applied to a plurality of rows of a display matrix; and

(iv) said plurality of orthogonal addressing functions is represented by an orthogonal block-circulant matrix, the orthogonal block-circulant matrix comprising at least one sub-matrix;

(v) wherein at least one of said at least one sub-matrix is non-zero and non-orthogonal.

2. (Previously Presented) A method as defined in Claim 1, wherein there are row and column interchanges of said addressing functions.

3. (Cancelled)

3 ~~4~~. (Previously Presented) A method as defined in Claim 1, wherein said row (common) driving matrix is a block diagonal matrix, said block diagonal matrix comprising building blocks, and wherein all the building blocks are orthogonal block-circulant.

4 ~~5~~. (Previously Presented) A method as defined in Claim 3 ~~4~~, wherein said row (common) driving matrix is a row and column interchanged version of the row (common) driving matrix.

5 ~~6.~~ (Previously Presented) A method as defined in Claim 1, wherein said row (common) driving matrix comprises orthogonal block-circulant building blocks generated by using a paraunitary matrix.

6 ~~7.~~ (Previously Presented) A method as defined in Claim 5 ~~6~~, wherein said driving matrix is

$$\begin{bmatrix} 1 & 0 & 1 & 0 & -1 & 0 & 1 & 0 \\ -1 & 0 & -1 & 0 & -1 & 0 & 1 & 0 \\ -1 & 0 & 1 & 0 & 1 & 0 & 1 & 0 \\ -1 & 0 & 1 & 0 & -1 & 0 & -1 & 0 \\ 0 & 1 & 0 & 1 & 0 & -1 & 0 & 1 \\ 0 & -1 & 0 & -1 & 0 & -1 & 0 & 1 \\ 0 & -1 & 0 & 1 & 0 & 1 & 0 & 1 \\ 0 & -1 & 0 & 1 & 0 & -1 & 0 & -1 \end{bmatrix}.$$

7 ~~8.~~ (Previously Presented) A method as defined in Claim 1, wherein said row (common) driving matrix is based on orthogonal block-circulant building blocks generated by nonlinear programming.

8 ~~9.~~ (Previously Presented) A method as defined in Claim 7 ~~8~~, wherein said row (common) driving matrix is based on order-4 orthogonal block-circulant building blocks.

10. (Previously Presented) A method as defined in Claim 7 ~~8~~, wherein said row (common) driving matrix is based on order-8 orthogonal block-circulant building blocks.

9 ~~11.~~ (Currently Amended) A ~~protocol~~ <u>method</u> as defined in Claim 8 ~~9~~, wherein said building blocks comprise:

(1)

$$\begin{bmatrix} 1 & 1 & -1 & 1 \\ 1 & 1 & 1 & -1 \end{bmatrix};$$

(2)

$$\begin{bmatrix} -1 & 1 & 1 & 1 \\ 1 & 1 & 1 & -1 \end{bmatrix};$$

(3)

$$\begin{bmatrix} -1 & 1 & -1 & -1 \\ 1 & 1 & -1 & 1 \end{bmatrix};$$

(4)

$$\begin{bmatrix} -1 & -1 & -1 & 1 \\ 1 & 1 & -1 & 1 \end{bmatrix};$$

(5) all alternatives of (1)-(4) generated by

(i) sign inversion (i.e., $-E$);

(ii) row interchange, i.e.,

$$\begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} E;$$

(iii) circulant shift of E, i.e.,

$$ER_{4,2};$$

and any combinations of (i)-(iii).

11 ~~12.~~ (Currently Amended) A ~~protocol~~ method as defined in Claim 10, wherein said building blocks comprise

(1)

$$\begin{bmatrix} 1 & 1 & -1 & 1 & 1 & -1 & 1 & 1 \\ 1 & 1 & 1 & -1 & 1 & -1 & -1 & -1 \end{bmatrix};$$

(2)

$$\begin{bmatrix} 1 & 1 & 1 & -1 & 1 & -1 & -1 & -1 \\ 1 & 1 & 1 & 1 & -1 & 1 & 1 & -1 \end{bmatrix},$$

(3)

$$\begin{bmatrix} 1 & 1 & -1 & -1 & -1 & 1 & -1 & -1 \\ 1 & 1 & 1 & 1 & -1 & 1 & 1 & -1 \end{bmatrix},$$

(4)

$$\begin{bmatrix} 1 & 1 & -1 & 1 & -1 & 1 & -1 & -1 \\ 1 & 1 & 1 & 1 & 1 & -1 & -1 & 1 \end{bmatrix},$$

(5)

$$\begin{bmatrix} -1 & 1 & -1 & 1 & 1 & -1 & -1 & 1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix},$$

(6)

$$\begin{bmatrix} -1 & 1 & -1 & 1 & -1 & 1 & 1 & -1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix},$$

(7)

$$\begin{bmatrix} -1 & 1 & -1 & 1 & 1 & 1 & -1 & -1 \\ 1 & 1 & 1 & 1 & -1 & 1 & 1 & -1 \end{bmatrix},$$

(8)

$$\begin{bmatrix} -1 & 1 & 1 & -1 & 1 & -1 & 1 & -1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix};$$

(9)

$$\begin{bmatrix} -1 & 1 & 1 & 1 & 1 & 1 & 1 & -1 \\ 1 & 1 & -1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(10)

$$\begin{bmatrix} -1 & 1 & -1 & 1 & -1 & 1 & 1 & -1 \\ 1 & 1 & -1 & -1 & -1 & -1 & -1 & -1 \end{bmatrix};$$

(11)

$$\begin{bmatrix} -1 & 1 & 1 & -1 & -1 & -1 & -1 & -1 \\ 1 & 1 & -1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(12)

$$\begin{bmatrix} 1 & -1 & -1 & 1 & -1 & 1 & -1 & 1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix};$$

(13)

$$\begin{bmatrix} 1 & -1 & -1 & 1 & 1 & -1 & 1 & -1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix};$$

(14)

$$\begin{bmatrix} 1 & -1 & 1 & -1 & 1 & -1 & -1 & 1 \\ 1 & 1 & 1 & 1 & 1 & 1 & -1 & -1 \end{bmatrix};$$

(15)

$$\begin{bmatrix} 1 & -1 & -1 & 1 & -1 & -1 & -1 & -1 \\ 1 & 1 & 1 & -1 & 1 & -1 & -1 & -1 \end{bmatrix},$$

(16)

$$\begin{bmatrix} 1 & -1 & 1 & -1 & 1 & 1 & -1 & -1 \\ 1 & 1 & 1 & 1 & 1 & -1 & -1 & 1 \end{bmatrix},$$

(17)

$$\begin{bmatrix} 1 & -1 & 1 & 1 & 1 & 1 & -1 & 1 \\ 1 & 1 & 1 & -1 & 1 & -1 & -1 & -1 \end{bmatrix},$$

(18)

$$\begin{bmatrix} 1 & 1 & -1 & 1 & 1 & 1 & 1 & -1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix},$$

(19)

$$\begin{bmatrix} 1 & 1 & 1 & -1 & 1 & 1 & -1 & 1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix},$$

(20)

$$\begin{bmatrix} 1 & 1 & -1 & 1 & 1 & 1 & 1 & -1 \\ 1 & -1 & 1 & 1 & 1 & -1 & -1 & -1 \end{bmatrix},$$

(21)

$$\begin{bmatrix} 1 & 1 & 1 & -1 & 1 & 1 & -1 & 1 \\ 1 & -1 & 1 & 1 & 1 & -1 & -1 & -1 \end{bmatrix};$$

(22)

$$\begin{bmatrix} -1 & 1 & 1 & 1 & 1 & -1 & 1 & 1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(23)

$$\begin{bmatrix} -1 & -1 & -1 & 1 & 1 & -1 & -1 & -1 \\ 1 & 1 & -1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(24)

$$\begin{bmatrix} -1 & 1 & -1 & -1 & 1 & -1 & -1 & -1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(25)

$$\begin{bmatrix} 1 & -1 & 1 & 1 & -1 & 1 & 1 & 1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(26)

$$\begin{bmatrix} 1 & -1 & -1 & -1 & -1 & 1 & -1 & -1 \\ -1 & 1 & 1 & 1 & -1 & 1 & -1 & -1 \end{bmatrix};$$

(27)

$$\begin{bmatrix} 1 & -1 & 1 & -1 & 1 & 1 & -1 & -1 \\ -1 & 1 & 1 & -1 & -1 & -1 & -1 & -1 \end{bmatrix};$$

(28) all alternatives of (1)-(27) generated by

(i) sign inversion (i.e., $-E$);

(ii) row interchange, i.e.,

$$\begin{bmatrix} 0 & 1 \\ 1 & 0 \end{bmatrix} E \, ;$$

(iii) circulant shift of E, i.e.,

$$ER_{8,2i} \, ;$$

for i=1, 2, or 3, and any combinations of (i)-(iii).

12 ~~13.~~ (Previously Presented) A liquid crystal display, wherein there is a driving scheme, and a method as defined in Claim 1.